

# **FL-AX 132 IP54** rev.0 del 14/12/04

## **Preliminary Data**

TIPO	COPPIA Nm	POTENZA Kw	VELOCITA' rpm	TENSIONE V	CORRENTE A	COS $\Phi$	Eff.	
132.1	<b>125,5</b>	<b>13,8</b>	1050	400	27,6	0,86	0,84	<b>1000 RPM</b>
132.2	<b>170,7</b>	<b>18,0</b>	1010	400	36,1			
132.3	<b>204,1</b>	<b>22,2</b>	1041	400	44,5			
132.4	<b>274,2</b>	<b>29,0</b>	1010	400	58,0			
132.5	<b>340,4</b>	<b>38,5</b>	1080	400	77,0			
132.1	<b>120,5</b>	<b>18,9</b>	1500	400	37,0	0,84	0,88	<b>1500 RPM</b>
132.2	<b>162,9</b>	<b>26,1</b>	1530	400	51,0			
132.3	<b>196,0</b>	<b>31,2</b>	1520	400	61,0			
132.4	<b>258,5</b>	<b>41,9</b>	1550	400	82,0			
132.5	<b>323,6</b>	<b>51,2</b>	1510	400	100,0			
132.1	<b>117,3</b>	<b>24,8</b>	2020	400	48,0	0,83	0,90	<b>2000 RPM</b>
132.2	<b>158,9</b>	<b>33,6</b>	2020	400	65,0			
132.3	<b>191,2</b>	<b>42,6</b>	2130	400	82,5			
132.4	<b>252,5</b>	<b>57,9</b>	2190	400	112,0			
132.5	<b>315,6</b>	<b>72,4</b>	2190	400	140,0			