

# FL-AX 160 IP54

rev.0.1 del 18/10/05

## Preliminary Data

TIPO	COPPIA Nm	POTENZA Kw	VELOCITA' rpm	TENSIONE V	CORRENTE A	COS $\Phi$	Eff.	
160.1	<b>315</b>	<b>33</b>	1000	400	59,0	0,92	0,87	<b>1000</b> <b>RPM</b>
160.2	<b>359</b>	<b>38</b>	1010	400	69,0			
160.3	<b>430</b>	<b>46</b>	1020	400	83,0			
160.4	<b>491</b>	<b>53</b>	1030	400	95,0			
160.5	<b>539</b>	<b>57</b>	1010	400	103,0			
160.1	<b>289</b>	<b>46</b>	1520	400	83,5	0,90	0,89	<b>1500</b> <b>RPM</b>
160.2	<b>335</b>	<b>54</b>	1540	400	97,0			
160.3	<b>397</b>	<b>64</b>	1540	400	116,0			
160.4	<b>452</b>	<b>70</b>	1480	400	126,0			
160.5	<b>509</b>	<b>80</b>	1500	400	143,0			
160.1	<b>284</b>	<b>61</b>	2050	400	106,0	0,90	0,92	<b>2000</b> <b>RPM</b>
160.2	<b>329</b>	<b>75</b>	2180	400	131,0			
160.3	<b>389</b>	<b>84</b>	2060	400	147,0			
160.4	<b>446</b>	<b>98</b>	2100	400	171,0			
160.5	<b>491</b>	<b>107</b>	2080	400	187,0			